

KF850T & KF850J Processor Settings

November 13, 2001



KF850T triamp

KF850J triamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Mid	Hi
4.0	2.0	-3.5
0.00	0.00	0.55
Positive	Positive	Positive
40	257	1580
24	24	24
Butterworth	Linkwitz-Riley	Butterworth
257	1580	16000
24	24	24
Linkwitz-Riley	Linkwitz-Riley	Butterworth
50	343	6161
6.0	3.5	-1.0
Parametric	Parametric	Parametric
2.00	6.73	2.00
0.50	0.15	0.50
	707	1490
	3.0	2.8
	Parametric	Parametric
	2.00	4.24
	0.50	0.24
	459	11980
	-2.0	9.0
	Parametric	Parametric
	5.04	4.24
	0.20	0.28

Low	Mid	Hi
4.0	1.0	-5.0
0.00	0.00	0.50
Positive	Positive	Positive
40	257	1580
24	24	24
Butterworth	Linkwitz-Riley	Butterworth
257	1580	thru
24	24	
Linkwitz-Riley	Linkwitz-Riley	
50	324	3090
6.0	3.0	1.5
Parametric	Parametric	Parametric
2.00	5.04	2.00
0.50	0.20	0.50
	445	7330
	-3.0	-3.0
	Parametric	Parametric
	5.04	5.99
	0.20	0.17
	687	12690
	3.0	13.0
	Parametric	Parametric
	3.00	2.52
	0.33	0.59

NOTE: To use systems with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.